


Bluetooth® Wireless Earphone MXH-BTW500

User manual

Thank you for purchasing this MAXELL product. Before use, make sure to read this Instruction Manual and use the product correctly and safely

Contents of the package



Charging Case

Charging Cable (USB-A-USB Mirco-B approx, 25cm) x 1pc

User Manua

Document)


(This

Ouick Star

Guide

Earpieces (XS/S/M/L 2pcs each)

* M is attached to the main unit



Introduction

About the user manual

- This Instruction Manual may be subject to change without prior notice.
- In order to improve the product, external appearance or part of the specifications may be subject to change without prior notice.

Disclaimer (See the warranty certificate for details of the warranty.)

- Maxell shall not be responsible for any damage caused by fires. earthquakes, action of a third party, any accidents, intended or unintended misuse or other usage under abnormal conditions.
- The warranty stated in the warranty certificate is all we warrant, and we do not warrant anything except for this warranty including express warranty and implied warranty
- Maxell shall not be responsible for failure due to any damage caused by usage other than described in the instruction manual
- This product is not being designed to be any equipment or device which could be concerned with human life such as medical device, nuclear device, astronomical device, transportation device etc., nor equipment or devices which requires high reliability. In case this product is used for the above equipment and or systems, Maxell do not responsible for any injuries or fire accident cause by the failure of this product.
- This product is Japanese specification. We assume no responsibility if use outside Japan

2 Safety Caution

Please strictly follow If it is handled incorrectly, the user may suffer A Danger death or severe injury^{*1} and the urgency is high. Warning If it is handled incorrectly, it is assumed that the user may suffer death or serious injury'1. If it is handled incorrectly, it is assumed that the user / Caution may suffer minor injury'2 or there is a possibility that property damage*3 may occur."



*1: Severe injury is indicated by those that have after effects such as

If the charging is not completed even after exceeding the predetermined charging time, stop charging It may cause leakage, overheating, fire or breakage.

A Caution

Do not increase the volume too much

Continuously listening to loud volume can result in overstimulation of ears for an extended period of time. It may affect the hearing. \bigcirc Furthermore, if the volume is raised too much from the beginning, the sudden loud sounds may harm ears. Before using, please reduce the volume of the connected device.

Discontinue use when it does not fit your skin

Continued usage may cause irritation or rash. 0 If you feel an abnormality, please discontinue use and seek medical attention

Do not force the earphones into your ear

It may hurt your ear hole.

Charge and use within the temperature range of 5~40°C

Charging and using at temperatures outside this range may cause leakage, overheating, breakage, or malfunction.


Make sure the USB connector does not get dusty

|--|

Note on wireless use


This device uses 2.4 GHz frequency band. This frequency band is also used by internal radio stations (radio stations that requires a license), specific low-power radio stations (radio stations that do not require a license) and amateur radio stations (radio stations that requires a license) for moving object identification that are used in industrial, scientific, and medical equipment such as microwave ovens as well as factory manufacturing lines.

- 1. Before using this device, make sure that any internal radio station, any specific low power radio station or any amateur radio station for moving object identification are not operated nearby.
- 2. In the unlikely event of radio interference to an internal radio station for moving object identification from the device, immediately change the location of use or stop the emission of radio waves.
- 3. In addition, when any troubles arise such as radio interference to a specific low-power radio station or an amateur radio station for moving object identification from this unit happened, please contact our company's "Customer Service Center".
- 4. This unit is certified as a low-power data communication system based on the Radio Law. Therefore, you do not need a wireless station license to use this machine. However, it is prohibited to disassemble, remodel or erase the certification making on the product.
- 5. Please do not use in areas where use of mobile phone and wireless equipment is prohibited such as in hospitals or priority seat of trains etc.
- 2.4FH1





B Name of Each Part



4 Preparation


 \bigcirc

0

This product has a built-in lithium ion battery. After purchase, please charge before use.


<Charging the charging case>

- 1. Connect the supplied USB charging cable to the charging case and the USB port of PC or USB adapter.
- 2. Charging of the charging case starts and indicator LED flashes. 3. Charging is completed when the indicator LED turns off. (Charging time: approx. 2.5hrs)
- 4. Remove the charging USB cable.



<Charging the main units>

- 1. Place the main units into the charging case. Align the L and R display of the main units to the corresponding indication in the charging case for charging.
- 2. The indicator LED on the main units turn red and charging starts. The indicator LED on the charging case shows an indication of the battery level
- 3. Charging is completed when the indicator lights on the main units go out. (Charging time: approx. 2hr)



- * Please do not use other cables except the supplied cable for charging * Connect the charging cable after checking the terminal direction carefully. If you connect incorrectly, the terminals may be damaged
- % Please use 5V DC power supply based on USB standard for a USB port. % If the battery is not used for a long period of time, charge it at least every 6 months. Self-discharge may cause complete discharge and may become unable to charge. * Lithium ion battery is a consumable item. The usage time will reduce with use. If the
- usage time becomes extremely short, it indicates the end of battery life. * It cannot be operated while charging.
- * When the battery level of the main units become low, the guidance sound "battery low" will be announced from the unit.

<Choosing an earpiece>



At the time of purchase, size M earpiece are attached to the main unit. If size M does not fit your ears, please replace with the size XS, S or size L earpiece in the contents

If the earpiece does not fit correctly, it will not be possible to seal the ear hole with the earpiece, which may cause sound leakage and no bass to be heard. Also, if you feel that the volume is low, there is a possibility of sound leakage

5 How To Use


<Pairing and connecting>

In order to use this product, it is necessary to pair with your device. Once pairing is done, you can connect without pairing again.

- 1. When the main units (L) and (R) are removed from the charging case, the main units power turns on automatically, and the indicator LED starts flashing.
- 2. After a while, the LED of the main unit (L) starts to flash red and blue alternately.^{*1} The main unit (R) flashes red and blue alternately, and then changes to a slow blue flash.
- 3. Enable Bluetooth function on your Bluetooth device. % For details on setting, please refer to the instruction manual of the device.
- 4. Please select "MXH-BTW500" from the list displayed on your Bluetooth device.

5. When pairing is completed, the blue indicator LED flashes slowly.

*1: When pairing is performed for the first time after purchase, it will be in paring mode immediately after the power is turned on. When paring the second device, it will be in pairing mode approximately 30 seconds after the power is turned on.



<Connection after the second time onward>

1. When the main units are removed from the charging case, the main units' power turns on automatically, and the indicator LED start flashing.

- 2. Activate Bluetooth on your Bluetooth device.
- 3. The earphone will connect automatically.*2 After connect, the display lamp will flash blue slowly.
- *2: If it does not connect automatically, please select "MXH-BTW500" from the list displayed on your device.

Caution

- Pairing mode lasts for approximately 3 minutes, and if it is not paired during that time, the power will OFF.
- Password^{*3} input may be requested by your Bluetooth device. In that case, you can pair it by entering "0000".
- This product can simultaneously store up to 6 paired Bluetooth devices. When more than 7 pairings are attempted, the information of the 1st stored Bluetooth device is erased and is replaced by the newly paired device. If you want to use a Bluetooth device whose information has been erased, please pair it again.
- *3: Password may be called passcode, passkey, PIN code, etc.

<How to operate>

Common function

Function	Operation	Display lamp	Guidance sound
	Remove the main units from the charging case	Main Unit L: Blue light flashes	
Power On	Or, while the power is off, press and hold the multi function button on the main unit L and R for approximately 3 seconds	Main Unit R: Blue light and Red light flash alternatively, after that, Blue light flashes slowly	Power On Left Channel Right Channel

	Place the main units into the charging case	Main Unit LR: Red light ON	Power OFF	
Power OFF	Or, press and hold the multi function button on the main unit L or R for approximately 3 seconds	Main Unit LR: Light OFF		
	Remove the main units from the charging case	Main unit L: Blue light flashes →	Power ON Left Channel Right Channel Pairing Mode	
Pairing Mode	Or, while the power off, press and hold the multi button on the main unit L for about 5 seconds After pairing the main unit L, the main unit R turns on the power by pressing and holding the multi button for about 3 seconds	Blue light and Red light flash alternatively Main unit R: Blue light and Red light flash alternatively		
Pairing complete	Pair this product from your Bluetooth device. Please refer to <pairing and="" connecting=""></pairing>	Main unit LR: Blue light flashes slowly	Connected	
Connect	After pairing is completed, automatically connects if Bluetooth of your Bluetooth device is enabled ^{*4}	Main unit LR: Blue light flashes slowly	Connected	
Disconnect	Disconnect the product from your device (or disable Bluetooth)	Main unit LR: Blue light flashes slowly	Disconnected	

*4: If it does not connect automatically, please select "MXH-BTW500" from the Caution After approx. 3 minutes without Bluetooth connection, the power will

turns off automatically.

Music Playback

Function	Operation	
PLAY / PAUSE	Press the multi function button on the main unit L or R to operate play and pause	
Volume UP / DOWN This operation cannot be done with this product. Operate with the connected de		
Next song (skip to the next song)	Press the multi function button on main unit L or R twice in succession	
Previous song (return to the beginning of the currently playing song ¹⁵) Press the multi function button on main uni L or R three times in succession		
*5: If the button is pressed at the beginning of the song, it will skip to the previous		

song

Caution Depending on your device, the operation may different or may not be available

Hands free call

Function	Operation	
Receiving a call Press the multi function button on the main unit L or R receiving a call		
Ending a call	Press the multi function button on the main unit L or R during a call	
	The other party disconnects the call	

Caution Depending on your device, the operation may different or may not be available

6 Troubleshooting

The power does not turn on	 Insert the main units into the charging case and remove them from the charging case. Press and hold down the multi function button for about 3 seconds. Please charge the product. 	
No sound	 Please pair and connect Bluetooth. Power is not turned on. Press and hold the multi funtion button for approximately 3 seconds. Check to see if the connected device supports Bluetooth profile A2DP. Check if the connected device is playing. Please increase the volume of the Bluetooth device slowly. 	
Sound is distorted or interrupted	 Please reduce the volume of the connected device and this unit. Please turn off the functions such as bass boost of connection device. Remove any obstacles between the connection device and this unit. Keep the connection device close to this unit. Please keep away from radio equipment or microwave ovens. 	
Cannot hear the voice on the phone	 Please press the multi function button to receive the call. Make sure that the Bluetooth device supports HFP or HSP. 	
Unable to charge	 Insert the charging cable to the charging terminal completely. Remove the main units from the charging case and place the main units in again. 	

Remove dirt from the main units and charging case contacts. • Charge within the charge temperature range (5°C to 40°C).

If the problem does not improve, please reset the main units. When the main units are reset, all paired device information is erased and it will be in the state at the time of purchase. Please pair again.

1. Press and hold the multi function button on the main unit L or R for approximately 3 seconds to turn the power off.

- 2. Press and hold the multi function buttons of the main units L for approximately 15 seconds, and release when the purple indicator LED flashes and turn off
- 3. Press and hold the multi function buttons of the main units R for
- approximately 15 seconds, and release when the purple indicator LED flashes and turn off.
- 4. Set the main units L and R in the charging case.

5. Please carry out pairing according to the procedure in **5** How to Use <Pairing and connecting>.

7 Specification

	Туре	Sealed dynamic type
	Driver unit	Diameter 6mm
	Audio frequency response	20~20,000Hz
	Power supply	Built-in rechargeable lithium ion battery
General	Duration	Continuous playback: approx. 4.5 hours, Continuous standby: approx. 100 hours.
		Charging case charge main units for approx. 2.5 times ^{*1}
specification	Charging time	Main Unit: Approx. 2 hours
		Charging Case: Approx. 2.5 hours
	Weight	Main Unit: Approx. 5g x 2 Charging Case: Approx. 31g
	Accessories	Earpieces (XS/S/M/L 2 units each) % M size are attached to the main units. Charging cable (USB-A-USB Micro-B approx. 25cm) x1, instruction manual, Quick start guide
Wireless specification	Communication method	Bluetooth [®] Ver.5.0
	Communication distance	Max. 10m
	Supported profile	A2DP, AVRCP, HFP
	Supported codecs	SBC
	Supported content protection	SCMS-T
	Multi-paring	Max. up to 6 units

*1: When the main units and the charging case are fully charged, the max. playback time is 15 hours, where 1 time by the charged main units and 2.5 times by charging from the charging case. Total 3.5 times.

Specifications and appearances are subject to change without prior notice for improvement %This device has a lithium ion battery built in. Usage time and battery charging time are based on our test results. It depends on the usage environment.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Maxell Asia, Ltd. is under license.

8 Discard this product

A Caution Disposal of rechargeable batteries in Japan



The built-in rechargeable battery can be recycled. Do not remove the rechargeable battery yourself, please contact our Customer Service Center. Please refer to the JBRC website for information on rechargeable battery collection / recycling and recycling partners.

Maxell. Ltd. 30-13 Motoyoyogi-Cho, Shibuya-Ku, Tokyo 151-8527 http://www.maxell.co.jp

PA1529-00